

RCP16 Plug-in socket receiver PULSE

The RCP16 plug-in socket receiver receives codes from paired secwave transmitters, and activates the pulse output, e.g. a garage door motor, for 1 second. Up to 200 transmitters can be memorised in total.




RCP16S5001A02-01K

Technical specifications

Coding	secwave, AES 128-bit encryption Up to 200 transmitters can be programmed. Not compatible with Easywave products!
Frequency	868.30 MHz
Channels	1
Power supply	230 V AC, 50 Hz
Power consumption	0.2 W standby 0.8 W relay switched (without load)
Operating mode	PULSE (1 second)
Outputs	1 potential-free relay contact (normally open)
Maximum contact load D/A/NL/S/N	pulse output: 1 A / 24 V DC mains voltage (not switchable): 10 A / 230 V AC
Operating temperature	-10 °C to +35 °C
Dimensions	50 x 120 x 75 mm
Color	white similar to RAL 9003

Plug system



Scope of delivery

- Plug-in socket receiver
- Operating manual

Models

Product numbers	Description	Plug system
RCP16S5001A02-01K	Plug-in socket receiver secwave 868 MHz PULSE, white, 230V	D/A/NL/S/N