

RCL03 Low-voltage mini receiver

The RCL03 mini receiver is used above all to upgrade existing systems.

Its two potential-free relay contacts make it possible to upgrade a wide variety of systems with a radio interface. Converting a garage door motor is just as easy as integrating Easywave transmitters in complex home call systems.

The RCL03 is powered by 12-24 V AC/DC and can be programmed with up to 32 transmission codes.



RCL03E5002B01

Technical specifications

Coding	Easywave Up to 32 transmitters can be programmed.
Frequency	868.30MHz
Channels	2
Power supply	12-24V AC/DC
Power consumption	0.4W standby at 24V DC 0.8W standby at 24V AC
Operating modes	DEADMAN (maximum 36 seconds) ON/OFF (2-button operation) PULSE (1 second) ROLLER BLIND MOTOR CONTROL (2-button operation) ROLLER BLIND MOTOR CONTROL (3-button operation)
Inputs	2 external buttons
Outputs	2 potential-free relay contacts (changeover contacts)
Maximum contact load	
- AC	24V / 1A / 24VA
- DC	30V / 1A / 30W
Operating temperature	-20 °C to +60 °C
Dimensions (W/L/H)	70/64/35 mm
Color	white similar to RAL 9003

Scope of delivery

- Mini receiver
- Adhesive pad
- Operating manual

Models

Product numbers	Description
RCL03E5002B01	Mini receiver, Easywave, 12-24V, 2x changeover, potential-free, white

Wiring diagram

