

RCP25 Plug-in socket pager

The RCP25 plug-in socket pager emits a visual and acoustic signal. When the signal of an Easywave radio transmitter is detected, the set ringtone sounds.

The ringtone continues to repeat cyclically until receipt of the signal is acknowledged by a transmitter or directly on the pager itself.

Die Lautstärke ist in drei Stufen einstellbar und gilt für alle eingelernten Sender. Ein LED-Blitzlicht kann optional zugeschaltet werden.

The RCP25 is also able to analyze undervoltage telegrams signaling that the batteries in compatible radio transmitters are too low.

Energy efficient: The RCP25 consumes only 0.2 W in standby mode.



RCP25E5001A01K

Technical specifications

Coding	Easywave 32 call codes and 32 acknowledgment codes can be programmed.
Frequency	868.30 MHz
Channels	1
Melodies	12
Power supply	230 V AC, 50 Hz (Schuko plug)
Power consumption	0.2 W standby
Volume	at a distance of 30 cm: 80 dB (soft) 85 dB (medium) 90 dB (loud)
Operating temperature	-20 °C to +35 °C
Dimensions (H/W/D)	71.4/71.4/75.5 mm
Color	white similar to RAL 9003

Scope of delivery

- Plug-in socket pager
- Operating manual

Models

Product numbers	Description
RCP25E5001A01K	Plug-in socket pager 1-channel, white