

RT42 Hand transmitter

The RT42 hand transmitter is a wireless transmitter which transmits the secwave code at the push of a button, and activates the secwave wireless receiver according to the selected mode.

The transmitter has a battery control function which checks the battery capacity. If the battery capacity is low, the LED flashes after the transmitter button is released.



RT42S5004A01-21K

Technical specifications

Coding	factory coding with secwave telegram, AES 128-bit encryption Not compatible with Easywave products!
Frequency	868.30 MHz
Channels	4
Range	typically 150 m in good free-field conditions
Power supply	1x 3V battery, CR2032
Operating indicator	LED
Operation	transmission lasts as long as the button is pressed (maximum 36 seconds)
Function	depends on the receiver (see models)
Operating temperature	-20 °C to +60 °C
Dimensions	37 x 61.5 x 10.7 mm
Weight	30 g (including battery)
Color	black similar to RAL 9005

Scope of delivery

- Hand transmitter including battery
- Operating manual

Models

Product numbers	Description	Function
RT42S5004A01-21K	Hand transmitter secwave 868 MHz 4-channel black with metal bracket	4x PULSE